

Datasheet
4011001

Lichtschiene Luxi Link 20W Netzteil

Das **LUXI LINK** 20W Netzteil mit Netzanschlusskabel ist das Kraftwerk des LUXI LINK-Systems. Mit 180cm Zuleitung lässt sich das Netzteil genau dort verbauen, wo Sie es hinhaben möchten. Die Länge der Zuleitung zur Lichtschiene beträgt 150cm.

Zum direkten Anschluss an die Lichtschienen wird noch ein Schalter oder Zuleitung benötigt.

Zusatzinformation:

Abmessung = 50 x 90 x 30mm
Max. Schienenlänge = 1.150mm



220-240 V	AC Voltage
50-60 Hz	Frequency Range
100-265 V	Voltage Range AC
V	Voltage Range DC
mA	AC Current
20,00 W	Rated Power
%	Full Load Efficiency
	Power Factor
W	Power at Standby
	Inrush Current
	Dimming method
Hz	Radio frequency
0 kHz	PWM-frequency
0 V	Output voltage
0 %	Voltage Tolerance
0 W	Output Power
A	Output Current
mA	Constant Current range
0 °C	Ambient Temperature
0 °C	Storage Temperature
0 °C	Max. Housing Temp.
IP	Ingress Protection Code
0	Protection Class
0 %	Total Harmonic distortion
h	Calculated Lifetime
40000 h	Lifetime
3 a	Guarantee
mm	Dimensions
mm	width
mm	height
g	Weight
Nein	Shortcircuit proof
Nein	Overtemperature protection
Nein	Overvoltage Protection
	Switching cycles



as of: 02.03.2023

